

ASe Processor Settings

November 13, 2001



AS300e biamp

| OUTPUT | Name | Low | Mid/Hi |
|----------|-------------|-------------|----------------|
| GAIN | (dB) | 4.0 | 0.0 |
| DELAY | (ms) | 0.00 | 0.08 |
| POLARITY | | Positive | Positive |
| HPF | Freq (Hz) | 40.5 | 445 |
| | Slope (dB) | 24 | 24 |
| | Shape | Butterworth | Linkwitz-Riley |
| LPF | Freq (Hz) | 385 | thru |
| | Slope (dB) | 24 | |
| | Shape | Butterworth | |
| PEQ1 | Freq (Hz) | 50 | 1542 |
| | Level (dB) | 6.0 | -4.0 |
| | Type | Parametric | Parametric |
| | Q | 2.00 | 1.12 |
| | (Bandwidth) | 0.50 | 0.89 |
| PEQ2 | Freq (Hz) | 216 | 971 |
| | Level (dB) | -2.5 | -1.5 |
| | Type | Parametric | Parametric |
| | Q | 5.34 | 3.56 |
| | (Bandwidth) | 0.19 | 0.28 |
| PEQ3 | Freq (Hz) | 167 | 612 |
| | Level (dB) | 3.5 | 1.0 |
| | Type | Parametric | Parametric |
| | Q | 5.34 | 2.00 |
| | (Bandwidth) | 0.19 | 0.50 |
| PEQ4 | Freq (Hz) | 545 | 6169 |
| | Level (dB) | -7.0 | -2.0 |
| | Type | Parametric | Parametric |
| | Q | 3.17 | 3.56 |
| | (Bandwidth) | 0.33 | 0.28 |
| PEQ5 | Freq (Hz) | | 5040 |
| | Level (dB) | | 2.0 |
| | Type | | Parametric |
| | Q | | 4.24 |
| | (Bandwidth) | | 0.24 |

NOTE: To use system with sub, high pass LF @ 80 Hz (24 dB Butterworth) & do not use PEQ 1.