

# FL103 Processor Settings

January 2, 2006



## FL103 bi-amp

OUTPUT		Name	LF	MF/HF
GAIN	(dB)		-1.0	0.0
DELAY	(ms)		0.55	0.00
POLARITY			Positive	Positive
HPF	Freq (Hz)		25	250
	Slope (dB)		24	24
	Shape		Butterworth	Butterworth
LPF	Freq (Hz)		250	thru
	Slope (dB)		24	
	Shape		Butterworth	
PEQ1	Freq (Hz)		35	6720
	Level (dB)		3.0	3.0
	Type		Parametric	Parametric
	Q		2.00	3.00
	(Bandwidth)		0.50	0.33
PEQ2	Freq (Hz)		76.5	472
	Level (dB)		2.0	-2.5
	Type		Parametric	Parametric
	Q		2.00	3.00
	(Bandwidth)		0.50	0.33
PEQ3	Freq (Hz)			3460
	Level (dB)			2.0
	Type			Parametric
	Q			5.99
	(Bandwidth)			0.17
PEQ4	Freq (Hz)			6530
	Level (dB)			2.7
	Type			Parametric
	Q			5.99
	(Bandwidth)			0.17
PEQ5	Freq (Hz)			728
	Level (dB)			1.7
	Type			Parametric
	Q			1.50
	(Bandwidth)			0.67

NOTE: To use system with sub, high pass LF @ 100 Hz (24 dB Butterworth) & do not use PEQ 1.

Output gains assume all amplifiers have the same voltage gain